

TITLE OF THE INVENTION

FOCUS ADJUSTMENT APPARATUS, CONTROL METHOD THEREFOR,
AND MEDIUM FOR SUPPLYING CONTROL PROGRAM THEREFOR

5 FIELD OF THE INVENTION

The present invention relates to a focus
adjustment apparatus for an image sensing apparatus
such as a digital camera or video camera, a control
method therefor, and a medium for supplying the control
10 program therefor.

BACKGROUND OF THE INVENTION

Conventionally, as the automatic focusing
function (to be referred to as the AF function
15 hereinafter) of a camera, a hill-climbing scheme has
been proposed by, e.g., Japanese Patent Laid-Open
No. 62-103616 and known. In recent years, as image
sensing apparatuses used for video cameras, 3-CCD type
apparatuses used by broadcasting stations or for
20 operational use have been widely used. Accordingly,
the image quality increasingly improves, and the
focusing accuracy is also rapidly increasing. This
tendency is expected to be strong in the future.

For lenses as well, along with intensive
25 competition for values added and discriminations, the
magnification becomes high, and the AF accuracy of a

lens is required to be high.

However, in the conventional image sensing apparatus, the high image quality by the 3-CCD scheme and the high magnification of a lens are inconsistent from the viewpoint of improvement of the (AF) function. This is a very important subject of study.

Since a lens has chromatic aberration due to its optical characteristics, all color components do not always form images on the same plane. More specifically, in the 3-CCD scheme in which a light beam from an object is separated by a prism or the like into three primary colors: red (R), green (G), and blue (B), the CCDs have different focus positions. Especially, a zoom lens capable of changing its magnification can hardly focus all chromatic aberrations at the respective zoom positions onto the same plane and is impractical.

In recent years, a higher magnification is required. Conversely, as the magnification increases, the chromatic aberration tends to be enlarged. An enlarged chromatic aberration means that, for example, even when a green object is in focus, red and blue objects on the same plane separate from the best focus state due to the high magnification.

25 In some systems, an attachment lens is attached
to the front portion of a lens, or the camera and lens

are interchangeable. Abundant accessories including an extender or tube attached between the camera and the lens to convert the magnification or change the optical characteristics are also important as products. A lens
5 portion including such an accessory attached to the lens is called a lens system. The accessory largely influences the chromatic aberration in the lens system.

Hence, for the conventional AF control, a high focus accuracy is required for a high image quality,
10 while AF at the best focus position cannot be obtained because the chromatic aberration is enlarged due to the high magnification.

SUMMARY OF THE INVENTION

15 It is an object of the present invention to provide an apparatus such as a focus adjustment apparatus capable of appropriately adjusting focusing with respect to chromatic aberration, a control method therefor, and a medium for supplying the control
20 program therefor.

In order to achieve the above object, according to the present invention, there is provided an apparatus such as a focus adjustment apparatus comprising a color component signal forming circuit for
25 forming a plurality of color component signals corresponding to predetermined different color

09649123 " 082800

components of object light received through an optical system and a focus adjustment signal forming circuit for forming a signal for focus adjustment on the basis of a signal formed by changing a ratio of the plurality of color component signals formed by the color component signal forming circuit.

According to the present invention, there is also provided a focus adjustment method comprising the steps of forming a plurality of color component signals corresponding to predetermined different color components of object light received through an optical system, and forming a signal for focus adjustment on the basis of a signal formed by changing a ratio of the plurality of color component signals formed.

According to the present invention, there is also provided a medium such as a storage medium for supplying a focus adjustment control program, the control program comprising forming a plurality of color component signals corresponding to predetermined different color components of object light received through an optical system, and forming a signal for focus adjustment on the basis of a signal formed by changing a ratio of the plurality of color component signals formed.

Other features and advantages of the present invention will be apparent from the following

description taken in conjunction with the accompanying drawings, in which like reference characters designate the same or similar parts throughout the figures thereof.

5

BRIEF DESCRIPTION OF THE DRAWINGS

Fig. 1 is a functional block diagram showing an image sensing apparatus according to the first embodiment of the present invention;

09649128 082800
10 Figs. 2A-1 to 2C-3 are graphs showing signal characteristics so as to explain the process of setting the mixing ratio of video signals in accordance with chromatic aberration information, in which Figs. 2A-1 to 2A-3 are graphs showing lens chromatic aberrations in the wide-angle state, middle state, and telephoto state, respectively, Figs. 2B-1 to 2B-3 are graphs showing AF signal characteristics in the wide-angle state, middle state, and telephoto state, respectively, when the video signal mixing ratio is uniform, and Figs. 2C-1 to 2C-3 are graphs showing AF signal
15 characteristics in the wide-angle state, middle state, and telephoto state, respectively, when the video signal mixing ratio changes;
20

Fig. 3 is a graph showing the mixing ratio based on the lens chromatic aberration;

25

Fig. 4 is a flow chart showing the control processing procedure of the first embodiment;

Fig. 5 is a functional block diagram showing an image sensing apparatus according to the second embodiment of the present invention;

Figs. 6A-1 to 6C-3 are graphs showing signal characteristics when the F-number is F1.8 so as to explain the process of setting the mixing ratio of video signals in accordance with chromatic aberration information, in which Figs. 6A-1 to 6A-3 are graphs showing lens chromatic aberrations in the wide-angle state, middle state, and telephoto state, respectively, Figs. 6B-1 to 6B-3 are graphs showing AF signal outputs in the wide-angle state, middle state, and telephoto state, respectively, when the video signal mixing ratio is uniform, and Figs. 6C-1 to 6C-3 are graphs showing AF signal characteristics in the wide-angle state, middle state, and telephoto state, respectively, when the AF signal mixing ratio changes;

Figs. 7D-1 to 7E-3 are graphs showing signal characteristics when the F-number is F16 so as to explain the process of setting the mixing ratio of video signals in accordance with chromatic aberration information, in which Figs. 7D-1 to 7D-3 are graphs showing lens chromatic aberrations in the wide-angle state, middle state, and telephoto state, respectively, and Figs. 7E-1 to 7E-3 are graphs showing AF signal characteristics in the wide-angle state, middle state,

and telephoto state, respectively, when the video signal mixing ratio is uniform;

Fig. 8 is a graph showing the mixing ratio based on the lens chromatic aberration and F-number;

5 Fig. 9 is a flow chart showing the control processing procedure of the second embodiment;

Fig. 10 is a functional block diagram showing an image sensing apparatus according to the third embodiment of the present invention;

10 Fig. 11 is a flow chart showing the control processing procedure of the third embodiment;

Fig. 12 is a flow chart showing the control processing procedure of the fourth embodiment;

15 Fig. 13 is a flow chart showing the control processing procedure of the fifth embodiment;

Fig. 14 is a functional block diagram showing an image sensing apparatus according to the sixth embodiment of the present invention;

20 Fig. 15 shows graphs of signal characteristics so as to explain the process of setting the mixing ratio of video signals in accordance with chromatic aberration information;

Fig. 16 is a graph showing the mixing ratio based on the lens chromatic aberration;

25 Fig. 17 is a flow chart showing the control processing procedure of the sixth embodiment;

Fig. 18 is a functional block diagram showing an image sensing apparatus according to the seventh embodiment of the present invention;

Fig. 19 is a flow chart showing the control
5 processing procedure of the seventh embodiment;

Fig. 20 is a functional block diagram showing an image sensing apparatus according to the eighth embodiment of the present invention; and

Fig. 21 is a flow chart showing the control
10 processing procedure of the eighth embodiment.

DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS

The preferred embodiments of the present invention will be described below with reference to the
15 accompanying drawings.

(First Embodiment)

Fig. 1 is a block diagram showing the first embodiment of the present invention. Referring to Fig. 1, reference numeral 1 denotes an optical system
20 comprising a rear focus zoom lens (RFZ lens) having four lens groups. The RFZ lens 1 comprises a first lens group (front element) 101 as a fixed lens group, a second lens group (variator) 102 as a movable lens group having a variable magnification function, a third
25 lens group (afocal) 103 as a fixed lens group, and a fourth lens group (RR) 104 as a movable lens group

having a focusing function and a function as a compensator for correcting an imaging plane variation due to the variable magnification. Each lens group is actually constructed by a plurality of lenses, though
5 the number of lenses of each lens group is not particularly limited.

008280" 82764960
The image of a light beam from an object is formed on a photoelectric conversion element as an image sensing means such as a CCD. The photoelectric
10 conversion element comprises image sensing elements 2-1, 2-2, and 2-3 which are located on the monochromatic light emerging surface sides of prisms 21-1, 21-2, and 21-3 as color separation means, respectively. A blue
- (B) component of the three primary colors is reflected
15 by the blue reflecting dichroic film of the prism 21-3 and forms an image on the image sensing element 2-3. A red (R) component is reflected by the red reflecting dichroic film of the prism 21-1 and forms an image on the image sensing element 2-1. A green (G) component
20 is transmitted through the prisms 21-1, 21-2, and 21-3 and forms an image on the image sensing element 2-2.

An aperture member 3 adjusts the amount of light incident on an photoelectric conversion element 2. An aperture driving unit 4 drives the aperture member 3
25 under the control of a control circuit 7 such that a predetermined amount of light is incident on the

microcomputer or the like causes the apparatus to perform the AF operation in accordance with the AF signal from the AF signal generation circuit 14 and the output from the chromatic aberration information

5 storage section 15. The chromatic aberration information storage section 15 and AF section 16 are included in the control circuit 7. As the AF scheme, the hill-climbing scheme has been proposed and known, and a detailed description thereof will be omitted.

10 In the AF operation, the R, G, and B components do not always form images at the best focus position on the same imaging plane because of the chromatic aberrations of lenses and the positions of the image sensing elements 2-1, 2-2, and 2-3.

15 For a zoom lens, generally, the aberration is small in the wide-angle state, though the aberration becomes large in the telephoto state. In the wide-angle state, optimum AF can be performed using a signal generated from all the R, G, and B video signal
20 components. However, in the telephoto state, the AF operation may not sufficiently function due to the aberration.

In the present invention, the chromatic aberration (MTF) of each lens is prepared as
25 information in advance. In accordance with the chromatic aberration information, the focus position is

described below are merely examples for a descriptive convenience and are not limited to those values.

Fig. 2A-2 shows a state wherein the R, G, and B components do not form images at the best peak position on the same plane and are separated from each other due to the chromatic aberrations in the middle region. As shown in Fig. 2B-2, if the R, G, and B mixing ratio is $G : R : B = 1 : 1 : 1$, two peaks as AF signals are present at two points: a point near the G and B components and a point corresponding to the R component, and the AF operation may stop at one of the peak positions. Generally, a video signal contains the G component at a high ratio, so the G peak position is close to the best focus position for the human eye. Hence, the more the position where the AF operation stops is separated from the G component, the larger the defocus state becomes.

As shown in Fig. 2C-2, when the mixing ratio of the R, G, and B components is set to $G : B : R = 1 : 1 : 0.3$, the peaks can converge to one point, so the focus position can be detected on the basis of the signal component which is contained in the video signal at a high ratio. When the signal component ratio in the video signal is known in advance, it can be determined which color component signal is to be used as a major component for AF signal generation.

Fig. 2A-3 shows a state wherein no best peak position is obtained on one imaging plane because of the chromatic aberrations in the telephoto region. AF signal peaks based on the R, G, and B video signal components are present on different imaging planes. As shown in Fig. 2B-3, if the mixing ratio of the R, G, and B components is $G : B : R = 1 : 1 : 1$, peaks as AF signals are present at the R, G, and B positions, and the AF operation may stop at one of the peak positions.

10 As shown in Fig. 2C-3, when the mixing ratio is set to $G : B : R = 1 : 0.5 : 0.1$, the peaks can converge to one point, so the focus position can be detected on the basis of the signal component which is contained in the video signal at a high ratio.

15 Fig. 3 is a graph showing a detailed example of a
change in mixing ratio on the basis of the magnitudes
of positional shifts of the R and B components with
respect to the G component due to chromatic aberrations.

For example, if the ratio of the G component is
1.0, ratios are obtained from an aberration $\Delta G-R$
between the G and R components and an aberration $\Delta G-B$
between the G and B components, and the ratio G : R : B
is set to 1 : 1 : 1 or 1 : 0 : 0. These ratios may be
prepared as a table in the control circuit 7 or
calculated. The detailed numerical values are not
limited to those described above, and the values may be

000000"02764960

externally rewritten.

For a zoom lens (RFZ lens 102), the chromatic aberration changes depending on the zoom position. For this reason, when chromatic aberrations corresponding to the zoom positions are stored in the chromatic aberration information storage section 15 in advance, the AF operation can be performed at an appropriate mixing ratio G : R : B for any zoom position.

The control processing procedure of the first embodiment will be described with reference to the flow chart shown in Fig. 4. In step S1, the control circuit 7 receives lens position information of the RFZ lens 102 and the like from the lens position detection circuit 23. In step S2 (to be simply referred to as S2 hereinafter), the control circuit 7 receives pieces of chromatic aberration information corresponding to the pieces of lens position information read in S1 from the chromatic aberration information storage section 15. In S3, the control circuit 7 calculates the AF generation ratio of the R, G, and B components. In S4, the calculation result obtained in S3 is output to the process circuit 13. In S5, the AF signal generation circuit 14 generates an AF signal from the calculation result. In S6, the control circuit 7 causes the AF section 16 to receive the output from the process circuit 13. In S7, the AF section 16 executes

chromatic aberrations in the wide-angle state at an F-number of F1.8. In this case, the shifts between the R, G, and B components are small. Hence, as shown in Fig. 6B-1, even when the ratio of the R, G, and B

5 components of the AF signal is 1 : 1 : 1, only one peak position is obviously present. However, since the R, G, and B components do not completely match, the gradient of the output peak of the AF signal is almost flat, and the actual peak position can hardly be detected by the
10 AF operation. As shown in Fig. 6C-1, when the mixing ratio of the R, G, and B components is set to G : B : R = 1 : 0.9 : 0.8, the peak can easily be detected.

Fig. 6A-2 shows a state wherein the R, G, and B components do not form images at the best peak position
15 on the same plane in the middle region at an F-number of F1.8, the G and B components are close to each other, and the R component is separated. As shown in Fig. 6B-2, if the ratio of components is G : B : R = 1 : 1 : 1, two peaks as AF signals are present at two
20 points: a point near the G and B components and a point corresponding to the R component, and the AF operation may stop at one of the peak positions. Generally, a video signal contains the G component at a high ratio, so the G peak position is close to the best focus
25 position for the human eye. Hence, the farther the position where the AF operation stops is separated from

the G component, the larger the defocus state becomes. As shown in Fig. 6C-2, when the mixing ratio of the R, G, and B components is set to 1 : 1 : 0.3, the peaks can converge to one point, so the focus position can be
5 detected on the basis of the signal component which is contained in the video signal at a high ratio. When the signal component ratio in the video signal is known in advance, it can be determined which color component signal is to be used as a major component for AF signal
10 generation.

Fig. 6A-3 shows a state wherein no best peak position is obtained on one imaging plane because of the chromatic aberrations in the telephoto region at an F-number of F1.8. AF signal peaks based on the R, G,
15 and B video signal components are present on different imaging planes. As shown in Fig. 6B-3, if the mixing ratio of the components is 1 : 1 : 1, peaks as AF signals are present at the R, G, and B positions, and the AF operation may stop at one of the peak positions.
20 As shown in Fig. 6C-3, when the mixing ratio is set to 1 : 0.5 : 0.1, the peaks can converge to one point, so the focus position can be detected on the basis of the signal component which is contained in the video signal at a high ratio.

25 When the F-number is F16, as shown in Fig. 7, the depth is larger than for F1.8 in all of the wide-angle

state shown in Fig. 7D-1, middle state shown in Fig. 7D-2, and telephoto state shown in Fig. 7D-3. Even when the mixing ratio of the R, G, and B components are set to 1 : 1 : 1, as shown in Figs. 7E-1, 5 7E-2, and 7E-3, to cover the aberrations between the R, G, and B components, one peak is output. Hence, this ratio is preferable for the AF signal.

As shown in Figs. 6 and 7, when the full-aperture state is almost set (small F-number), the mixing ratio 10 of the R, G, and B components is appropriately changed from 1 : 1 : 1 on the basis of the chromatic aberration information. As the stopped-down-aperture state is set (F-number becomes large), the mixing ratio is made close to 1 : 1 : 1. Thus, by changing the mixing ratio 15 in accordance with the F-number, an optimum AF signal is generated.

Fig. 8 is a graph showing a detailed example of a change in ratio on the basis of the magnitudes of positional shifts of the R and B components with 20 respect to the G component due to chromatic aberrations and F-number.

As is apparent from Fig. 8, when it is assumed that the ratio of the G component is 1.0, and the F-number is small, ratios are set low, or when the 25 F-number is large, ratios are set close to 1.0 even when the aberrations are equal in obtaining the ratios

embodiment will be described with reference to Fig. 10 and the flow chart shown in Fig. 11.

In S31, the first control circuit 7 receives lens position information of the RFZ lens 102 and the like
5 from a lens position detection circuit 23. In S32, the control circuit 7 receives pieces of chromatic aberration information corresponding to the pieces of lens position information read in S31 from a chromatic aberration information storage section 15. In S33, the
10 first control circuit 7 transmits the received chromatic aberration information to the camera unit 30. In S34, the second control circuit 17 calculates the AF generation ratio of the R, G, and B components on the basis of the received chromatic aberration information.
15 In S35, the calculation result obtained in S34 is output to the process circuit 13. In S36, an AF signal generation circuit 14 generates an AF signal from the calculation result. In S37, the second control circuit 17 receives the output from the process circuit 13. In
20 S38, the received AF signal is transmitted to an AF section 16 of the lens unit 20. In S39, the AF section 16 executes calculation for predetermined AF control. In S40, the AF section 16 performs focus driving on the basis of the calculation result obtained in S39.
25 As a conspicuous characteristic feature of this embodiment, the chromatic aberration information can be

used not only for the AF operation but also for various other application purposes.

(Fourth Embodiment)

5 The fourth embodiment will be described next with reference to Fig. 10.

09649128 082800
10 The fourth embodiment is almost the same as the third embodiment. The same reference numerals as in the third embodiment denote the same members in the fourth embodiment, and a detailed description thereof will be omitted. The fourth embodiment is different from the third embodiment in that aperture information of a zoom lens (RFZ lens 102) and the like are transmitted from a lens unit 20 to a camera unit 30, aperture information of the lens is also transmitted,
15 and the mixing ratio of R, G, and B components of an AF signal is calculated on the camera unit 30 side on the basis of the chromatic aberration information and F-number.

20 The control processing procedure of the fourth embodiment will be described with reference to Fig. 10 and the flow chart shown in Fig. 12.

25 In S41, a first control circuit 7 receives lens position information of the RFZ lens 102 and the like from a lens position detection circuit 23. In S42, the control circuit 7 receives pieces of chromatic aberration information corresponding to the pieces of

lens position information read in S41 from a chromatic aberration information storage section 15. In S43, the first control circuit 7 receives aperture information from an aperture detection circuit 6. In S44, the first control circuit 7 transmits the received chromatic aberration information and aperture information to the camera unit 30. In S45, a second control circuit 17 calculates the AF generation ratio of the R, G, and B components on the basis of the received chromatic aberration information in consideration of the aperture information. In S46, the second control circuit 17 outputs the calculation result obtained in S45 to a process circuit 13. In S47, an AF signal generation circuit 14 generates an AF signal from the calculation result. In S48, the second control circuit 17 receives the AF signal output from the process circuit 13. In S49, the received AF signal is transmitted to an AF section 16 of the lens unit 20. In S50, the AF section 16 executes calculation for predetermined AF control. In S51, the AF section 16 performs focus driving on the basis of the calculation result obtained in S50.

(Fifth Embodiment)

The fifth embodiment will be described next with
25 reference to Fig. 10.

The fifth embodiment is almost the same as the

third embodiment. The same reference numerals as in the third embodiment denote the same members in the fifth embodiment, and a detailed description thereof will be omitted. The fifth embodiment is different
5 from the third embodiment in that the mixing ratio of R, G, and B components for AF signal generation is calculated on the basis of optical information such as chromatic aberration information of a zoom lens (RFZ lens 102) and the like and aperture information, the
10 calculation result is transmitted to a camera unit 30, and the AF signal is generated on the camera unit 30 side.

The control processing procedure of the fifth embodiment will be described with reference to Fig. 10
15 and the flow chart shown in Fig. 13.

In S52, a first control circuit 7 receives lens position information of the RFZ lens 102 and the like from a lens position detection circuit 23. In S53, the control circuit 7 receives pieces of chromatic
20 aberration information corresponding to the pieces of lens position information read in S53 from a chromatic aberration information storage section 15. In S54, the first control circuit 7 receives optical information such as aperture information from an aperture detection
25 circuit 6. In S55, the first control circuit 7 calculates the AF generation ratio of R, G, and B

components on the basis of the received chromatic aberration information and optical information. In S56, the calculation result is transmitted to the camera unit 30. In S57, a second control circuit 17 outputs
5 the received calculation result to a process circuit 13. In S58, an AF signal generation circuit 14 generates an AF signal from the calculation result. In S59, the second control circuit 17 receives the AF signal output from the process circuit 13. In S60, the received AF
10 signal is transmitted to an AF section 16 of a lens unit 20. In S61, the AF section 16 executes calculation for predetermined AF control. In S62, the AF section 16 performs focus driving on the basis of the calculation result obtained in S61.

15 (Sixth Embodiment)

Fig. 14 is a block diagram showing the sixth embodiment.

A camera unit control circuit 217 of a camera unit transmits the output from a process circuit 213
20 for generating a focus signal for AF and the output for the aperture operation to a lens unit control circuit 207 through a camera contact 218 and adapter camera side contact 221, and an adapter lens side contact 222 and a lens contact 219. An adapter 220 has a contact
25 for identifying the pieces of information at the adapter lens side contact 222. The adapter 220

includes an identification circuit 223. The lens unit control circuit 207 identifies the presence/absence of the adapter and the type of adapter through the lens contact 219. The lens unit control circuit 207
5 performs the AF or aperture operation on the basis of these pieces of information and sends the zoom position, focus position, and aperture position to the camera unit control circuit by communication. Thus, the control circuits of the camera unit and lens unit can
10 transmit/receive information.

Referring to Fig. 14, reference numeral 201 denotes an optical system comprising a rear focus zoom lens (RFZ lens) having four lens groups. The RFZ lens 201 comprises a first lens group (to be referred to as
15 a front element hereinafter) 301 as a fixed lens group, a second lens group (to be referred to as a variator hereinafter) 302 as a movable lens group having a variable magnification function, a third lens group (to be referred to as an afocal hereinafter) 303 as a fixed
20 lens group, and a fourth lens group (to be referred to as an RR hereinafter) 304 as a movable lens group having a focusing function and a function as a compensator for correcting an imaging plane variation due to the variable magnification.

25 Each lens group is actually constructed by a plurality of lenses, though the number of lenses of

each lens group is not particularly limited. In addition, the adapter 220 is not particularly limited, and it may have or omit an optical system for, e.g., increasing the zoom magnification, an optical system
5 for obtaining a closeup object sensing effect, a means for converting data without using any optical system by directly passing a light beam, or a flange-back adapter.

The image of a red (R) component of the three primary colors of a light beam from an object is formed
10 on an image sensing element 202-1 such as a CCD, the image of a green (G) component is formed on an image sensing element 202-2 such as a CCD, and the image of a blue (B) component is formed on an image sensing element 202-3 such as a CCD.

15 An aperture member 203 adjusts the amount of light incident on an photoelectric conversion element 202. An aperture driving unit 204 drives the aperture member 203 under the control of the control circuit 207 such that a predetermined amount of light is incident
20 on the photoelectric conversion element 202. Reference numeral 205 denotes an aperture position detector. A detection circuit 206 detects the output from the aperture position detector 205 and outputs the signal to the control circuit 207.

25 Driving units 208 and 209 such as stepping motors drive the movable lens groups 302 and 304, respectively.

Drivers 210 and 211 drive the driving units 208 and 209, respectively.

An amplifier 212 amplifies the output from the photoelectric conversion element 202. A process

5 circuit 213 has an automatic focusing (to be referred to as AF hereinafter) signal generation circuit 14 for converting a signal into a signal such as an NTSC video signal and mixing R, G, and B video outputs at an arbitrary ratio to generate an AF signal for the AF

10 operation. A storage means 215 stores chromatic aberration information of each lens in advance. When the adapter 220 is attached, the storage means 215 may have chromatic information including information of the adapter 220. Alternatively, when the adapter is

15 attached, the chromatic aberration information may be calculated in the lens unit control circuit 207 on the basis of the information from the lens chromatic information storage means and the presence/absence of the adapter. An AF section 216 causes the apparatus to

20 perform the AF operation in accordance with the AF signal from the AF signal generation circuit 214 and the output from the chromatic aberration information storage means 215. The AF scheme is known, as

25 will be omitted.

In this embodiment, chromatic aberration of a

Fig. 15A-2 shows a state wherein the R, G, and B components do not form images at the best peak position on the same plane, the R and B components are close to each other, and the G component is separated

5 If the mixing ratio of the R, G, and B signal components is 1 : 1 : 1, two peaks as AF signals are present at two points: a point near the R and B components and a point corresponding to the G component, and the AF operation can stop at any peak position.

10 Generally, a video signal contains the G component at a high ratio, so the G peak position is close to the best focus position for the human eye. Hence, the farther the position where the AF operation stops is separated from the G component, the larger the
15 defocus state becomes.

As shown in Fig. 15C-2, when the mixing ratio is set to $G : B : R = 1 : 1 : 0.3$, the peaks can converge to one point, so the focus position can be detected on the basis of the signal component which is contained in
20 the video signal at a high ratio. When the signal component ratio in the video signal is known in advance, it can be determined which color component signal is to be used as a major component for AF signal generation.

Fig. 15A-3 shows a state wherein no best peak
25 position is obtained on one imaging plane because of the chromatic aberrations in the telephoto region. AF

008280" 82754960

signal peaks based on the R, G, and B video signal components are present on different imaging planes.

If the ratio is 1 : 1 : 1, peaks as AF signals are present at the R, G, and B positions, and the AF operation can stop at any peak position.

As shown in Fig. 15C-3, when the mixing ratio is set to $G : B : R = 1 : 0.5 : 0.1$, the peaks can converge to one point, so the focus position can be detected on the basis of the signal component which is contained in the video signal at a high ratio.

Fig. 16 is a graph showing a detailed example of a change in mixing ratio on the basis of the magnitudes of positional shifts of the R and B components with respect to the G component.

For example, if the ratio of the G component is 1.0, ratios are obtained from an aberration $\Delta G-R$ between the G and R components and an aberration $\Delta G-B$ between the G and B components, and the ratio $G : B : R$ is set to 1 : 1 : 1 or 1 : 0.0 : 0.0. These ratios may be prepared as a table in the control circuit or calculated. The detailed numerical values are not limited to those described above, and the values may be externally rewritten.

For a zoom lens, the chromatic aberration changes depending on the zoom position. For this reason, when chromatic aberrations corresponding to the zoom

positions are stored in advance, and pieces of
chromatic aberration information corresponding to the
zoom positions are stored, the AF operation can be
performed at an appropriate mixing ratio for any zoom
5 position.

Fig. 17 is a flow chart.

In S101, it is detected on the basis of the
signal from the identification circuit 222 whether the
adapter is attached between the lens and the camera,
10 and the type of adapter is detected if it is attached.
In S102, the zoom position information of the lens is
received. In S103, chromatic aberration information
corresponding to the detection result received in S101
and zoom position information received in S102 is
15 received. In S104, the AF generation ratio is
calculated. In S105, the calculation result obtained
in S104 is output. In S106, the AF signal is generated.
In S107, the output from the process circuit 213 is
received. In S108, calculation for predetermined AF
20 control is executed. In S109, focus driving is
performed on the basis of the calculation result
obtained in S108.

In this embodiment, an arrangement using image
sensing elements of 3-CCD scheme has been described.
25 However, an image formation position shift due to
chromatic aberration also occurs in a single CCD. AF

008280" 82164960

numerals as in the sixth embodiment will be omitted.

Referring to Fig. 18, an adapter 224 having an optical system is, e.g., a closeup lens for reducing the focusible object distance of the lens 201. A
5 detection circuit 225 detects whether the adapter 224 is attached. Upon detecting that the adapter 224 is attached to the front portion of the lens on the basis of the output from the detection circuit 225, a control circuit 207 obtains the chromatic aberration
10 information of the lens system including the lens 201 and adapter 224 on the basis of stored information or stored information and calculation. In accordance with the chromatic aberration information output, the AF signal generation ratio is calculated and generated to
15 execute AF control.

Fig. 19 is a flow chart.

In S121, the detection circuit 225 detects whether the adapter 224 is attached to the front portion of the lens. In S122, the zoom position
20 information of the lens is received. In S123, chromatic aberration information corresponding to the detection result received in S121 and zoom position information received in S122 is received. In S124, the AF generation ratio is calculated. In S125, the
25 calculation result obtained in S124 is output. In S126, the AF signal is generated. In S127, the output from

008280" 8264960

adapter 226 is attached in the lens, a control circuit 207 obtains the chromatic aberration information of the lens system including the lens 201 and adapter 226 on the basis of stored information or stored information
5 and calculation. In accordance with the chromatic aberration information output, the AF signal generation ratio is calculated and generated to execute AF control.

Fig. 21 is a flow chart.

In S131, the detection circuit 227 detects
10 whether the adapter 226 is attached in the lens. In S132, the zoom position information of the lens is received. In S133, chromatic aberration information corresponding to the detection result received in S131 and zoom position information received in S132 is
15 received. In S134, the AF generation ratio is calculated. In S135, the calculation result obtained in S134 is output. In S136, the AF signal is generated. In S137, the output from the process circuit 213 is received. In S138, calculation for predetermined AF
20 control is executed. In S139, focus driving is performed on the basis of the calculation result obtained in S138.

The present invention may be applied to a system constituted by a plurality of devices (e.g., a host
25 computer, an interface device, a reader, a printer, and the like) or an apparatus comprising a single device

(e.g., a copying machine, a facsimile apparatus, or the like).

005280" 82161960
09649128" 082800

The object of the present invention is realized even by supplying a medium such as a storage medium (or
5 recording medium) storing software program codes for realizing the functions of the above-described embodiments to a system or apparatus, and causing the computer (or a CPU or an MPU) of the system or apparatus to read out and execute the program codes stored in the
10 medium. In this case, the program codes read out from the medium realize the functions of the above-described embodiments by themselves, and the medium such as a storage medium storing the program codes constitutes the present invention. The functions of the above-described
15 embodiments are realized not only when the readout program codes are executed by the computer but also when the OS (Operating System) running on the computer performs part or all of actual processing on the basis of the instructions of the program codes.

20 The functions of the above-described embodiments are also realized when the program codes read out from the medium such as a storage medium are written in the memory of a function expansion board inserted into the computer or a function expansion unit connected to the
25 computer, and the CPU of the function expansion board or function expansion unit performs part or all of actual

008280" 82764950

processing on the basis of the instructions of the
program codes.

When the present invention is applied to the
medium such as a storage medium, it stores program
5 codes corresponding to the above-described flow chart
(shown in Fig. 4, 9, 11, 12, 13, 17, 19, or 21).

The embodiments of the present invention have
been described above. The present invention is not
limited to the contents disclosed in the above
10 embodiments and can be applied to any constitution as
long as it can implement the functions of the appended
claims or the functions of the embodiments.

For example, in the above embodiments, the AF
signal is formed in consideration of all the red, green,
15 and blue component signals. Only one (especially, the
green component signal) or two color component signals
may be used to form the AF signal, as needed.

The separated color component signals may be
different from those of the above embodiments, as
20 needed.

In the above embodiments, the separated color
component signals are resynthesized, and then, the AF
signal is formed. Instead, the AF signal may be formed
before or without resynthesis.

25 In the above embodiments, the chromatic
aberration information of the adapter is used together

003230" 82T67950

with the chromatic aberration information of the optical system. However, only the chromatic aberration information of the adapter may be used, as needed.

In the above embodiments, the AF signal is used
5 to drive the optical system. However, the AF signal may be used for display.

The present invention may be applied to only the optical system, only the image sensing apparatus to which the optical system is attached, or both the
10 optical system and the apparatus to which the optical system is attached.

The software and hardware configurations of the above embodiments can be appropriately replaced.

The present invention may be implemented by
15 combining the above embodiments or the technical element thereof as needed.

In the present invention, all or some of the appended claims or embodiments may form one apparatus, be connected to another apparatus, or be an element of
20 an apparatus.

The present invention can be applied to various cameras including an electronic camera such as a video camera capable of sensing a moving image or still image, a camera using a silver halide film, a camera whose
25 image sensing lens is interchangeable, a single-lens reflex camera, a lens shutter camera, and a monitor

008280" 82464960

camera, an image sensing apparatus, optical apparatus,
or other apparatuses other than cameras, an apparatus,
method, and computer-readable storage medium applied to
the cameras, image sensing apparatus, optical apparatus,
5 or other apparatuses, and the elements thereof.

As has been described above, according to the
above-embodiment invention, an apparatus such as a
focus adjustment apparatus capable of appropriately
adjusting focusing in accordance with chromatic
10 aberration, a control method therefor, and a medium
such as a storage medium for supplying a control
program therefor can be provided.

As many apparently widely different embodiments of
the present invention can be made without departing from
15 the spirit and scope thereof, it is to be understood
that the invention is not limited to the specific
embodiments thereof except as defined in the appended
claims.